

Specifications

 [Expand / Collapse all](#)

Main Features

MIDI Control

Full assignable MIDI controls

PRO DJ LINK



Booth EQ



P-Lock Fader Caps



Auto Standby



DVS Control

-  rekordbox
-  Serato DJ Pro (Need to buy a license or subscription.)

Software System Requirements

Visit rekordbox.com for its specifications.

Visit serato.com for its specifications.

Bluetooth Audio Input

Wireless system : Bluetooth Ver.5.0

Maximum transmission distance : Approximately 10 m in unobstructed circumstances (Transmission distances are a guideline.)

Frequency band used : 2.4 GHz

Modulation method : FH-SS (Frequency Hopping Spread Spectrum)

Compatible Codecs : SBC, AAC

Wireless LAN

Supported standards : IEEE 802.11 a/b/g/n/ac

Frequency band used : 2.4 GHz / 5 GHz

Accessories

DJM-A9

Power Cord

Warranty (for some regions)

Quick Start Guide

Precautions for Use

Specifications

Dimensions (W x D x H)

407.4 x 107.9 x 458.3 mm

407.4 x 140.7 x 458.3 mm (when the wireless antenna stands upright)

Weight

10.2 kg

Sampling Rate

96 kHz

CH input A/D Converter

32 bit

MASTER, BOOTH, REC, SEND D/A Converter

32 bit

S/N Ratio Line

105 dB

S/N Ratio Phono

88 dB

S/N Ratio Mic

79 dB

Distortion

< 0.005 % (LINE)

Channels

EQ/ISO

3 band

EQ Range

Built-in, switchable 3-band equaliser: -26 dB ~ +6 dB dB

Performance Control

Channels

4

MULTI I/O

USB (Type A)

Sound Color FX

- Space
 - Dub Echo
 - Sweep
 - Noise
 - Crush
 - Filter
-

Beat FX

- Delay
 - Echo
 - Ping Pong
 - Spiral
 - Helix
 - Reverb
 - Flanger
 - Phaser
 - Filter
 - Triplet Filter
 - Trans
 - Roll
 - Triplet Roll
 - Mobius
-

Screen Display



X-PAD



rekordbox Quantize



Crossfader

Crossfader Type

Magvel Fader

Curve Assignable



Fader Curve

3

Mic

Mic Connection

- XLR / 1/4-inch Combo Jack
- 1/4-inch TRS Jack

Mic EQ

2 band

Mic EQ Range

-12 dB ~ +12 dB

Phantom power



Microphone Effects

- Echo
- Pitch
- Megaphone
- Reverb

Push-to-talk function



Talkover

Dedicated button

Talkover Attenuator



Terminals

Inputs

- 4 DIGITAL (Coaxial)
- 4 LINE (RCA)
- 4 PHONO (RCA)

Send/Return

- 1 SEND (1/4-inch TS jack)
- 1 RETURN (1/4-inch TS jack)

LAN

1

Outputs

- 1 MASTER (XLR, RCA)
- 1 BOOTH (1/4 inch TRS Jack)
- 2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)
- 1 REC OUT (RCA)
- 1 DIGITAL (Coaxial)

USB

- 1 USB A port
- 2 USB B ports
- 2 USB C ports

* The specifications and design of this product are subject to change without notice.

PRODUCTS

SUPPORT

NEWS

ABOUT US

© AlphaTheta Corporation

[Privacy policy](#)

[Terms of use](#)

[Cookie Policy](#)

[Trademarks](#)

[Cookies Settings](#)